



Project: _ _____ Quantity: _ Fixture Type: Customer:

Specifications

Material: All parts are durable 356 cast aluminum and high strength extruded

Shafts are available in 3" and 4" diameter and wall thickness of .125 or .188.

All hardware provided shall be stainless steel or zinc plated steel.

Mounting: Standard anchor bolts provided are 3/4" x 18" x 3". Bolts, nuts and washers shall be hot dipped galvanized steel.

Bolt pattern diameter is 9".

Access:

Access: Hand access opening and cover are provided in cast base. Hand hole cover is secured by two stainless steel machine screws. (Tamper-proof screws provided upon request). See drawing for position

4 1/2" bottom hole provided for conduit

Grounding:
All cast bases are provided with an aluminum grounding lug integrated to inner wall of shaft, 180 degrees to hand hole.
Grounding lug is drilled and tapped to accommodate %-20 stainless steel

Pole Height: Maximum pole height is 14 feet.

Finish: A polyester powder coat high quality finish is electro-statically applied and baked at 430° for exceptional durability and color retention. Products undergo an intensive five-step cleansing and pretreatment process for maximum paint adhesion.

Marine grade finish provides superior salt, humidity and UV protection. This coating withstands up to 3000 hours of continuous salt spray, comes with a 5-year warranty and is available in either a textured or gloss surface

Modifications:

Consult factory for custom or modified designs.

Catalog Logic	CB0201 -	4S14.188 -	GFI20 -	72 ,
	Cast Base	Shaft	Accessory	Finish

CB0201

1

2

3

Catalog Number

CB0201

Anchor Bolts: 3

Additional heights and pole diameters may be available. Contact factory for your specific needs.

Smooth Shaft Catalog No.	1 Fluted Shaft Catalog No.	Shaft Diameter	Finished Height	Wall Thickness
3S10.125	3F10.125	3"	10'	.125
3S11.125	-	3"	11'	.125
3S12.125	-	3"	12'	.125
-	-	-	-	-
3S12.188	3F12.188	3"	12'	.188
3S13.188	3F13.188	3"	13'	.188
-	-	-	-	-
4S10.125	-	4"	10'	.125
4S11.125	-	4"	11'	.125
4S12.125	-	4"	12'	.125
4S13.125	-	4"	13'	.125
4S14.125	-	4"	14'	.125
•	-	-	-	-
•	4F10.188	4"	10'	.188
-	4F11.188	4"	11'	.188
4S12.188	4F12.188	4"	12'	.188
4S13.188	4F13.188	4"	13'	.188
4S14.188	4F14.188	4"	14'	.188

GFI-S GFI-S GFI-WPU (20 amp GFCI receptacle outlet) GFI-WPU (20 amp GFCI receptacle with weather proof in-use cover) BAA (Cast Banner Arm A for 24" wide banner) BAB (Cast Banner Arm B for 30" wide banner) BAC (Cast Banner Arm C for 30" wide banner) LR1 (Cast Ladder Rest 1) LR3 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 4) LR5 (Cast Ladder Rest 5) SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN C (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	2	ACCESSORIES			
GFI-WPU (20 amp GFCI receptacle with weather proof in-use cover) BAA (Cast Banner Arm A for 24" wide banner) BAB (Cast Banner Arm B for 30" wide banner) BAC (Cast Banner Arm C for 30" wide banner) LR1 (Cast Ladder Rest 1) LR3 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 4) LR5 (Cast Ladder Rest 5) SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN C (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	GFI15	(15 amp GFCI receptacle outlet)			
proof in-use cover) BAA (Cast Banner Arm A for 24" wide banner) BAB (Cast Banner Arm B for 30" wide banner) BAC (Cast Banner Arm C for 30" wide banner) LR1 (Cast Ladder Rest 1) LR3 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 4) LR5 (Cast Ladder Rest 5) SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	GFI20	(20 amp GFCI receptacle outlet)			
BAB (Cast Banner Arm B for 30" wide banner) BAC (Cast Banner Arm C for 30" wide banner) LR1 (Cast Ladder Rest 1) LR3 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 4) LR5 (Cast Ladder Rest 5) SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN D (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	GFI-WPU				
BAB (Cast Banner Arm B for 30" wide banner) BAC (Cast Banner Arm C for 30" wide banner) LR1 (Cast Ladder Rest 1) LR3 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 4) LR5 (Cast Ladder Rest 5) SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN D (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	BAA	<u> </u>			
BAC (Cast Banner Arm C for 30" wide banner) LR1 (Cast Ladder Rest 1) LR3 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 4) LR5 (Cast Ladder Rest 5) SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN D (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)		192			
LR1 (Cast Ladder Rest 1) LR3 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 3) LR4 (Cast Ladder Rest 4) LR5 (Cast Ladder Rest 5) LR5 (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) LR5 (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) LR5 (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) LR5 (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) LR5 (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line) LR5 (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	BAB				
LR1 (Cast Ladder Rest 1) CODE LR3 (Cast Ladder Rest 3) CODE LR4 (Cast Ladder Rest 4) CODE LR5 (Cast Ladder Rest 5) CODE SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) CODE SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) CODE SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	BAC	(Cast Banner Arm C for 30" wide banner)			
LR4 (Cast Ladder Rest 4) DEMONDARY (Cast Ladder Rest 5) SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) TOUR SIGN SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) TOUR SIGN SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN B (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	LR1				
SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) TOUR SIGN SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) TOUR SIGN SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	LR3	(Cast Ladder Rest 3)			
SIGN A (Cast Sign A; 30" x 9", 8 letters/numbers on one line; requires Banner Arm to hang) SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	LR4	(Cast Ladder Rest 4)			
SIGN B (Cast Sign B; 31" x 7", 12 letters/numbers on one line; requires Banner Arm to hang) YOUR SIGN SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/ numbers on one line)	LR5	(Cast Ladder Rest 5)			
requires Banner Arm to hang) TOURSICN SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) YOUR SICN SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line)	SIGN A	requires Banner Arm to hang)			
SIGN C (Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang) VOUR SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line) VOUR SIGN	SIGN B	requires Banner Arm to hang)			
SIGN D (Cast Sign D; 11" x 6 1/2", 4 letters/numbers on one line) SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/numbers on one line) YOUR SIGN	SIGN C	(Cast Sign C; 27" x 11", two rows of 8 letters/numbers on each line, requires Banner Arm to hang)			
SIGN E (Cast Sign E; comes with pole clamp, 24 1/2" x 6", 9 letters/ numbers on one line) YOUR SIGN		~~ /L~~ L			
numbers on one line) YOUR SIGN	SIGN D				
FPH1 (Flag Pole Holder)	SIGN E	numbers on one line)			
	FPH1	(Flag Pole Holder)			

3 FINISHES							
Standard Grade	Marine Grade		Standard Grade	Marine Grade			
40	NA	Raw Unfinished	53	100	Copper Clay		
41	101	Black	56	109	Silver		
42	102	Forest Green	61	106	Black Verde		
43	114	Bright Red	70	118	Painted Chrome		
44	107	White	71	105	Painted Copper		
45	112	Bright Blue	72	108	Textured Black		
46	123	Sunny Yellow	73	125	Matte Black		
47	120	Aqua Green	76	121	Textured Architectural Bronze		
49	NA	Galvanized	77	127	Textured White		
50	111	Navy	78	124	Textured Silver		
51	103	Architectural Bronze	10	130	Aspen Green		
52	104	Patina Verde	11	131	Cantaloupe		
12	133	Lilac	13	132	Putty		
Consult factory for additional paint charges and availability							